
















		Material / Material	Max. Stromstärke / Max. current	Max. Spannung / Max. voltage	Leiterquerschnitte / Wire cross sections
FDFD1.25-250		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
FRD1.25-156		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
RV1.25-4		Messing / Brass	19A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
MPD1.25-156		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
RV1.25-5		Messing / Brass	19A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
MDD1. 25-250		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
RV1.25-6		Messing / Brass	19A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
FDD1. 25-250		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
BV1.25		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
PBDD1. 25-250		Messing / Brass	10A	380V	0.5-1.5 mm <sup>2</sup> / 22-16 AWG
FDFD2-250		Messing / Brass	15A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
FRD2-156		Messing / Brass	10A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
MDD2-250		Messing / Brass	15A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
MPD2-156		Messing / Brass	15A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
FDD2-250		Messing / Brass	15A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG

RV2-4		Messing / Brass	27A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
PBDD2-250		Messing / Brass	15A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
RV2-5		Messing / Brass	27A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
BV2		Messing / Brass	27A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
RV2-6		Messing / Brass	27A	380V	1.5-2.5 mm <sup>2</sup> / 16-14 AWG
FDFD5.5-250		Messing / Brass	19A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
FRD5.9-195		Messing / Brass	24A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
MDD5. 5-250		Messing / Brass	48A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
MPD5. 5-195		Messing / Brass	24A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
FDD5. 5-250		Messing / Brass	24A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
RV5-5.5		Messing / Brass	48A	380V	4-6 mm <sup>2</sup> / 12-10A.WG
PBDD5. 5-250		Messing / Brass	24A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
RV5.5-6		Messing / Brass	48A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
BV5.5		Messing / Brass	48A	380V	4-6 mm <sup>2</sup> / 12-10 AWG
RV5.5-8		Messing / Brass	48A	380V	4-6 mm <sup>2</sup> / 12-10 AWG